

DERIVADORES CON CONECTOR F DF 2XX / DF 4XX / DF 8XX

Factor de apantallamiento clase A
Paso de corriente en la línea troncal
5-2300 MHz

REFERENCIA		DF 212	DF 216	DF 220	DF 224	DF 412	DF 416	DF 420	DF 424	DF 816	DF 820	DF 824
Código		142001	142002	142003	142004	142005	142006	142007	142008	142009	142010	142011
Banda de paso	MHz	5-2400	5-2400	5-2400	5-2400	5-2400	5-2400	5-2400	5-2400	5-2400	5-2400	5-2400
Salidas	Nº	2	2	2	2	4	4	4	4	8	8	8
Atenuación de derivación	dB (+/-1)	12	16	20	24	12	16	20	24	16	20	24
Pérdidas de paso	dB 860 MHz db 2300 MHz	<2,2 <3,5	<1,6 <2,6	<1,1 <2,6	<1 <2,3	<3,2 <4,5	<1,8 <3,5	<1,5 <2,1	<1,3 <2	<3,8 <4,9	<1,9 <3,2	<1,4 <2,1
Desacoplo entre salidas	dB	>20	>20	>20	>20	>20	>20	>20	>20	>20	>20	>20
Perdidas de retorno	dB	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10	>10
Paso de corriente	mA	500	500	500	500	500	500	500	500	500	500	500



DF 2XX



DF 4XX



DF 8XX