PRODUCT-DETAILS

DDA802 A-63/0,03

DDA802A-63/0,03 2p 63A A 30mA



Información General

Extended Product Type	DDA802 A-63/0,03
Product ID	2CSB802101R1630
EAN	8012542920007
Catalog Description	DDA802A-63/0,03 2p 63A A 30mA
Long Description	The RCD Block DDA800 series assures protection to people and installations against fault current to earth. A large offer for standard instantaneous and selective AC and A types is completed with some configurations for special applications. This product is suitable for assembly with MCBs S800 series up to 63A.

Technical

Standards	IEC EN 60947-2 Ann. B
Operating Characteristic	Instantaneous
Type of Residual Current	A type
Rated Residual Current	30 mA
Rated Current (I_n)	63 A
Number of Poles	2
Power Loss	9 W
Rated Voltage (U_r)	230 V AC 240 V AC 400 V AC

Ambiente

Ambient Air Temperature	Funcionamiento -25...60 °C
RoHS Status	Following EU Directive 2011/65/EU

Technical UL/CSA

Short-Circuit Current Rating (SCCR)	0.03 ... 0.03 A

Dimensiones

Product Net Width	0.134 m
Product Net Height	0.108 m
Product Net Depth / Length	0.076 m
Product Net Weight	0.300 kg

Información de Embalaje

Package Level 1 Units	box 1 piece
Package Level 1 Width	0.115 m
Package Level 1 Height	0.094 m
Package Level 1 Depth / Length	0.136 m
Package Level 1 Gross Weight	0.4 kg
Package Level 1 EAN	8012542920007

Clasificación

Minimum Order Quantity	1 piece
Customs Tariff Number	85363030

Certificados y Declaraciones (Número de Documento)

Declaration of Conformity - CE	9AKK106713A5616
Environmental Information	document not needed
Instructions and Manuals	2CSB427001D0003

Descargas Populares

Data Sheet, Technical Information	2CSC400002D0209
Instructions and Manuals	2CSB427001D0003

Clasificaciones

Object Classification Code	Q
ETIM 4	EC002297 - Residual current circuit breaker (RCCB) module
ETIM 5	EC002297 - Residual current circuit breaker (RCCB) module
ETIM 6	EC002297 - Residual current circuit breaker (RCCB) module

Categorias

Productos y sistemas de baja tensión → Aparatos modulares de instalación → Interruptores diferenciales → Dispositivos diferenciales adaptables

